

TL1591 SAMPLE-AND-HOLD CIRCUIT FOR CCD IMAGERS

D3327, SEPTEMBER 1989

- 15-MHz Sampling Rate
- 30-ns Acquisition Time
- Diode-Bridge Switch
- 25-MHz Bandwidth
- Low-Voltage Supply

D OR P PACKAGE
(TOP VIEW)


T-77-17

ANLG V _{CC}	1	8	DGTL V _{CC}
ANLG IN	2	7	DGTL IN
ANLG GND	3	6	DGTL GND
ANLG OUT	4	5	SUB GND

description

The TL1591 is a monolithic integrated sample-and-hold circuit with excellent performance features using the BiFET process with Schottky-barrier diodes and designed for use with CCD area imagers. This device consists of an ultra-fast input buffer amplifier, a digital-controlled diode-bridge switch, and a high-impedance output buffer amplifier. The electronic switch is controlled by an LS-TTL-compatible logic input.

functional block diagram



2

CCD Image Sensors/Support Functions

PRODUCTION DATA documents contain information current as of publication date. Products conform to specifications per the terms of Texas Instruments standard warranty. Production processing does not necessarily include testing of all parameters.

TEXAS
INSTRUMENTS

POST OFFICE BOX 655303 • DALLAS, TEXAS 75265

Copyright © 1989, Texas Instruments Incorporated

2-89

TL1591
SAMPLE-AND-HOLD CIRCUIT FOR CCD IMAGERS

T-77-17

absolute maximum ratings over operating free-air temperature range (unless otherwise noted)

Supply voltage, V_{CC}	7 V
Digital input voltage	0 to V_{CC}
Continuous total dissipation	See Dissipation Rating Table
Operating free-air temperature range, T_A	-25°C to 80°C
Storage temperature range	-55°C to 150°C

DISSIPATION RATING TABLE

PACKAGE	$T_A \leq 25^\circ\text{C}$	DERATING FACTOR		$T_A = 80^\circ\text{C}$
	POWER RATING	ABOVE $T_A = 25^\circ\text{C}$		POWER RATING
D	725 mW	5.8 mW/°C		406 mW
P	1000 mW	8.0 mW/°C		560 mW

2

CCD Image Sensors/Support Functions

recommended operating conditions

	MIN	NOM	MAX	UNIT
V_{CC} Supply voltage	4.75	5	5.5	V
V_{IH} High-level digital input voltage	2			V
V_{IL} Low-level digital input voltage			0.8	V
V_{I-PP} Peak-to-peak analog input voltage			0.8	V

electrical characteristics over operating free-air temperature range (unless otherwise noted)

PARAMETER	TEST CONDITIONS	MIN	TYP†	MAX	UNIT
V_{IK} Input clamp voltage				-1.5	V
$V_{O,PP}$ Analog peak-to-peak output voltage			1.1		V
I_{IH} High-level input current	$V_{CC} = 5.5\text{ V}$, $V_{IH} = 2.7\text{ V}$			20	μA
I_{IL} Low-level input current	$V_{CC} = 5.5\text{ V}$, $V_{IL} = 0.4\text{ V}$	-0.28		-0.4	mA
I_O Analog output current			0.6		mA
I_{CC} Supply current	$V_{CC} = 5.5\text{ V}$		15	20	mA
r_i Input resistance			10		k Ω
r_o Analog output resistance			50		Ω

operating characteristics

PARAMETER	MIN	TYP†	MAX	UNIT
Linearity		0.7%	2%	
A_v Voltage amplification		0.8	0.9	V/V
Sample-to-hold offset error		15		mV
Sample-mode offset error		-50	50	mV
Hold-mode feedthrough			-50	dB
Hold-mode droop			100	$\mu\text{V}/\mu\text{s}$

† All typical values are at $V_{CC} = 5\text{ V}$, $T_A = 25^\circ\text{C}$.

TL1591

SAMPLE-AND-HOLD CIRCUIT FOR CCD IMAGERS

T-77-17

dynamic characteristics (see Figure 1)

PARAMETER	MIN	TYP†	MAX	UNIT
Acquisition time 0.6 V to 2% (see Note 1)		18		ns
Acquisition time 0.6 V to 1% (see Note 1)		31		ns
Hold-mode settling time (see Note 2)		35		ns
Sampling-mode bandwidth		25		MHz
Sampling rate			15	MHz

† All typical values are at V_{CC} = 5 V and T_A = 25°C.

PARAMETER MEASUREMENT INFORMATION




FIGURE 1. SAMPLE-HOLD DEFINITIONS

- NOTES: 1. Acquisition time is the time required, after the closing of the sampling switch, for the hold capacitor to charge to a full-scale voltage change and then remain within a specified error band around the final value.
2. Hold-mode settling time is the time from the hold command transition until the output has settled within a specified error band around the final value.

2

CCD Image Sensors/Support Functions

TL1591 SAMPLE-AND-HOLD CIRCUIT FOR CCD IMAGERS

T-77-17

PARAMETER MEASUREMENT INFORMATION




FIGURE 2. TEST CIRCUIT

TYPICAL CHARACTERISTICS




FIGURE 3. SAMPLE/HOLD ACCURACY VS COMMAND DURATION